Windows XP Driver Installation Procedure for DigiSwipe

When inserted into the PCMCIA slot, you should see this notification in the bottom right corner of the monitor.



After a few seconds, you should see the Found New Hardware Wizard screen.



Select 'Install from a list or specific location (Advanced)

Found New Hardware Wizard	
	Welcome to the Found New Hardware Wizard This wizard helps you install software for: TokenWorks_Inc. TokenWorks_CompactSwipe_Magnetic_Card_Reader If your hardware came with an installation CD or floppy disk, insert it now.
	What do you want the wizard to do? <ul> <li>Install the software automatically (Recommended)</li> <li>Install from a list or specific location (Advanced)</li> </ul> Click Next to continue.
	< <u>Back</u> Cancel

Select 'Don't Search. I will choose the driver to install'

Found New Hardware Wizard	
Please choose your search and installation options.	
O Search for the best driver in these locations.	
Use the check boxes below to limit or expand the default search, which includes local paths and removable media. The best driver found will be installed.	
Search removable media (floppy, CD-ROM)	
Include this location in the search:	
E:\ Browse	
Don't search. I will choose the driver to install.	
Choose this option to select the device driver from a list. Windows does not guarantee that the driver you choose will be the best match for your hardware.	
< <u>B</u> ack <u>N</u> ext> Cancel	

In the hardware Type, find the Ports hardware

Hardware Type.		E.
Select a hardware type, and then clic	ck Next.	
Common hardware types:		
Show All Devices		~
🤿 1394 Debugger Device		
Section 2 Class		
Computer		
Disnlay adapters		
		×
Les DVD / D.RUM drives		

## Highlight Ports (COM & LPT) and hit NEXT

Found New Hardware Wizard	
Hardware Type.	
Select a hardware type, and then click Next. Common <u>h</u> ardware types:	
Non-Plug and Play Drivers NT Apm/Legacy Support PCMCIA adapters PCMCIA and Flash memory devices PCMCIA (COM & LPT)	
<ul> <li>Printers</li> <li>Processors</li> <li>SBP2 IEEE 1394 Devices</li> <li>SCSL and BAID controllers</li> </ul>	
< <u>B</u> ack	<u>N</u> ext > Cancel

The following screen should display, MAKE Sure the Communication Port Model is selected if so, hit next

Found New Hardware Wizard			
Select the device driver you want to install for this hardware.			
Select the manufacturer and model of your hardware device and then click Next. If you have a disk that contains the driver you want to install, click Have Disk.			
(Standard port types)       Brother       Chase Research Plc.       Compaq GSM Radio Card	Communications Port  ECP Printer Port  Multiport Communications Port  Printer Port		
This driver is digitally signed. <u>Have Disk</u>			
	< <u>B</u> ack <u>N</u> ext > Cancel		

After hitting Next, the following warning will display. Hit YES



After a couple seconds, you should see the following screen

Found New Hardware Wizard	
Please wait while the wizard install	s the software
Communications Port	
Ď	8
	<pre>K Back Next &gt; Cancel</pre>

## Once completed, the following

Found New Hardware Wiza	ard
	Completing the Found New Hardware Wizard The wizard has finished installing the software for: Printer Port
	< <u>B</u> ack <b>Finish</b> Cancel

To verify installation and determine the com port,